

# Feed adapters with clamp ring



## Feed adapters with clamp ring



- Polished  $\leq Ra\ 0.8$ .
- To suit Piab feed station or transition pieces.

### Technical data, specific

Description	Part No.	Material	Weight lb
Feed adapter D=25, NBR, clamp ring	01.17.438	ASTM 316L, CuNi, NBR	5.32
Feed adapter D=25, Q clamp ring	01.17.439	ASTM 316L, CuNi, Q	5.35
Feed adapter D=32, NBR clamp ring	01.17.663	ASTM 316L, CuNi, NBR	5.70
Feed adapter D=32, Q clamp ring	01.17.664	ASTM 316L, CuNi, Q	5.70
Feed adapter D=40, NBR clamp ring	01.17.708	ASTM 316L, ASTM 304L, CuNi, NBR, POM	7.13
Feed adapter D=40, Q clamp ring	01.17.709	ASTM 316L, ASTM 304L, CuNi, Q, POM	7.15
Feed adapter D=50, NBR clamp ring	01.17.667	ASTM 316L, CuNi, NBR	9.13
Feed adapter D=50, Q clamp ring	01.17.668	ASTM 316L, CuNi, Q	9.15
Feed adapter D=75, NBR clamp ring	01.17.669	ASTM 316L, CuNi, NBR	17.5
Feed adapter D=75, Q clamp ring	01.17.670	ASTM 316L, CuNi, Q	17.5
Feed adapter D=100, NBR clamp ring	01.17.671	ASTM 316L, CuNi, NBR	28.3
Feed adapter D=100, Q clamp ring	01.17.672	ASTM 316L, CuNi, Q	28.3

### Dimensions

Description	D mm	H in	L1 in	L2 in	L3 in	G
Feed adapter, D=25	Ø 25x1.2	7.24	15.2	2.56	5.39-7.48	1/4"
Feed adapter, D=32	Ø 32x1.2	7.13	16.7	3.94	6.10-8.19	1/2"
Feed adapter, D=40	Ø 40x1.0	6.81	19.7	3.94	7.40-10.0	3/4"
Feed adapter, D=50	Ø 51x1.2	6.42	23.6	3.94	8.19-11.3	1"
Feed adapter, D=75	Ø 76.1x1.6	5.47	30.5	5.91	9.92-14.6	1 1/4"
Feed adapter, D=100	Ø 101.6x2.0	4.49	41.3	5.91	12.2-18.1	2"

## Ordering information

Description	Part No.
Feed adapter D=25, NBR, clamp ring	01.17.438
Feed adapter D=25, Q clamp ring	01.17.439
Feed adapter D=32, NBR clamp ring	01.17.663
Feed adapter D=32, Q clamp ring	01.17.664
Feed adapter D=40, NBR clamp ring	01.17.708
Feed adapter D=40, Q clamp ring	01.17.709
Feed adapter D=50, NBR clamp ring	01.17.667
Feed adapter D=50, Q clamp ring	01.17.668
Feed adapter D=75, NBR clamp ring	01.17.669
Feed adapter D=75, Q clamp ring	01.17.670
Feed adapter D=100, NBR clamp ring	01.17.671
Feed adapter D=100, Q clamp ring	01.17.672

